



**UNIVERSITI PUTRA MALAYSIA**

**CAPACITANCE-BASED TOMOGRAPHY OF FIBERBOARDS AND  
WOOD**

**ABDALLA IMHMED BABOH.**

**FS 2005 21**

# **CAPACITANCE-BASED TOMOGRAPHY OF FIBERBOARDS AND WOOD**

**By**

**ABDALLA IMHMED BAHBOH**

**Thesis Submitted to the School of Graduate Studies, Universiti Putra Malaysia,  
in Fulfilment of the Requirements for the Master of Science degree**

**May 2005**



## **DEDICATION**

**To My Parents  
My Wife, Son and Daughters,  
Brothers and Sisters**

**And**

**My Supervisor Professor Dr. Kaida Khalid  
&  
My Friend PhD. Student Lab-Mate Mr. Ghretli, Mohd  
For Their Guidance, Advice and Endless Supports**

Abstract of thesis presented to the Senate of Universiti Putra Malaysia in  
fulfilment of the requirement for the degree of Master of Science

## **CAPACITNCE BASED TOMOGRAPHY OF FIBERBOARDS AND WOOD**

**By**

**ABDALLA IMHMED BAHBOH**

**May 2005**

**Chairman: Professor Kaida Khalid, PhD**

**Faculty: Science**

In industry today, there is a need for designing modern instruments for quantitative and qualitative inspection of wood, wood-based materials and finished products. Development of technologies using electric fields requires a profound knowledge of the dielectric properties of wood. One of the promising techniques is the Electrical Capacitance Tomography (ECT).

Constructing a capacitive tomographic profile of wood and fiberboards has several applications in industry and agriculture. In this study a technique based on multi-frequency square-wave pulse signal is being used to probe the sample. The output signal is amplified, filtered and used to build property surface profiles for different local lumber samples. Analysis of the effect of different stimulating frequency on the overall contour shape of different samples is compared and the appropriate frequency is singled

out. Details on how this technique can be utilized to develop a capacitive sensor are also explained.

Two capacitive sensors were designed with different dimensions for the sensing plate.

The capacitive output of the sensors can be related to the different properties of the material under test (MUT). In this study, the sensors were tested for moisture content, thickness variations and local defects present in the sample material.

Both sensors were tested on local lumber samples and fiberboards. Contour plots were obtained for the output of the system, which represent the gradient changes in the wood moisture content as the probe moves across the material under test. The sensor with the smaller dimension probe proved to be superior in resolving the details of the sample and distinguishing the knots and defects of the sample. The larger probe is more accurate in determining the bulk moisture of the samples and more sensitive to thickness variations. The measurement accuracy of the moisture content percentage and thickness variation is about  $\pm 2.88\%$  and  $\pm 0.035$  cm respectively.

Even though the proposed sensors offer less accuracy than expensive LRC laboratory analyzers and limited in frequency selection and voltage input to MUT, nonetheless they are inexpensive to make, lighter in weight and can be easily implemented in –site or on-line processing.

Abstrak tesis yang dikemukakan kepada Senat Universiti Putra Malaysia sebagai memenuhi keperluan untuk ijazah Master Sains

## **TOMOGRAFI BEASID KAPASITANBAGI PAPAN SERAT DAN KAYU**

**Oleh**

**ABDALLA IMHMED BAHBOH**

**Mai 2005**

**Pengerusi: Professor Kaida Khalid, PhD**

**Fakulti: Sains**

Industri kini amat memerlukan rekabentuk peralatan moden untuk menyelia kualiti dan kuantiti kayu, bahan atau produk yang berasaskan kayu. Pembangunan teknologi yang melibatkan medan elektrik memerlukan pengetahuan asas tentang ciri-ciri dielektrik bagi kayu. Salah satu teknik yang boleh digunakan ialah teknik tomografi kapasitan elektrik (ECT).

Pembinaan profail tomografi kapasitan bagi kayu dan papan serat biasanya diaplikasi dalam indutri dan pertanian. Dalam kajian ini, teknik yang berasaskan isyarat denyut gelombang segiempat pada pelbagai frekuensi digunakan untuk menguji sampel. Nilai isyarat output yang telah dibesar, dan ditapis digunakan untuk membina bahan profail permukaan bagi sampel papan lapis tempatan dan satu frekuensi yang bersesuaian diperolehi. Perincian bagaimanapun teknik ini boleh digunakan untuk membangunkan pengesanan kapasitan juga turut disampaikan.

Dua pengesan kapasitan direka dengan bentuk berbeza sebagai plat pengesan. Output pengesan kapasitan boleh dihubungkan kepada ciri berbeza pada bahan yang diuji (MUT). Dalam kajian ini, alat diuji bagi mengesan kandungan kelengasan, variasi ketebalan, dan kecacatan tertentu pada bahan sampel.

Kedua-dua alat pengesan turut diuji pada sampel papan lapis dan papan serat. Plot kontur yang di perolehi untuk sistem output, mewakili perubahan gradian dalam kandungan kelembapan kayu apabila alat penguji digerakkan merentasi bahan yang diuji. Alat pengesan dengan penguji berdimensi kecil membuktikan ianya boleh digunakan untuk peleraian terperinci sesuatu sampel dengan menampakkan simpulan dan kecacatan pada sampel. Penguji berdimensi besar lebih jitu dalam menentukan luas kelembapan sampel dan lebih sensitif terhadap perubahan ketebalan. Kejituan pengukuran bagi kelengasan dan ketebalan masing-masing adalah  $\pm 2.88\%$  dan  $\pm 0.035$  cm.

Walaupun pengesan yang dicadangkan memperihalkan kejituan yang rendah berbanding pengenalisis makmal LRC yang mahal, voltan input dan pemilihan frekuensi yang tehad kepada bahan yang diuji, tetapi ianya murah untuk dibina, lebih ringan dan mudah diimplimentasi dalam sebarang pemprosesan.

## ACKNOWLEDGEMENTS

First and foremost, I would like to express my deepest praise to ALLAH who has given me the strength, faith, confidence and courage to complete this project.

It is my pleasure to acknowledge my supervisor, **Professor Dr. Kaida Khalid** for his guidance, help, advice and suggestions throughout the duration of my project. I also would like to extend my sincere appreciation to my co-supervisor Professor Dr. Mohd. Hamami Sahri and Dr. Jumiah Hassan for their help and discussion during my studies

Special thanks are also given to PhD. Student and my lab-Mate Mr. Mohammed Mustafa Ghretli, for his helping ideas, encouragement and support; lab assistant of Department of Physics, Mr. Roslim for his help.

Credit is also given to anyone, especially my family, and friends, who either directly or indirectly, has contributed in a variety of ways towards the success of the work.



I certify that an Examination Committee met on 12<sup>th</sup> May 2005 to conduct the final examination of Abdalla Imhmed Bahboh on his Master of Science thesis entitled “Capacitance-based Tomography of Fiberboards and Woods” in accordance with Universiti Pertanian Malaysia (Higher Degree) Act 1980 and Universiti Pertanian Malaysia (Higher Degree) Regulations 1981. The Committee recommends that the candidate be awarded the relevant degree. Members of the Examination Committee are as follows:

**Elias Saion, PhD**  
Associate Professor  
Faculty of Science  
Universiti Putra Malaysia  
(Chairman)

**Wan Mohamad Daud Wan Yusoff, PhD**  
Associate Professor  
Faculty of Science  
Universiti Putra Malaysia  
(Internal Examiner)

**Sidek Ab. Aziz, PhD**  
Associate Professor  
Faculty of Science  
Universiti Putra Malaysia  
(Internal Examiner)

**Sahrim Ahmad, PhD**  
Professor  
Faculty of Science and Technology  
Universiti Kebangsaan Malaysia  
(External Examiner)



**GULAM/RUSUL RAHMAT ALI, PhD**  
Professor/Deputy Dean  
School of Graduate Studies  
Universiti Putra Malaysia

Date: 20 JUN 2005

This thesis submitted to the Senate of Universiti Putra Malaysia and has been accepted as fulfilment of the requirements for the Master of Science degree. The members of the Supervisory Committee are as follows:

**KAIDA KHALID, PhD**

Professor  
Faculty of Science  
Universiti Putra Malaysia  
(Chairman)

**MOHD. HAMAMI SAHRI, PhD**

Professor  
Faculty of Forestry  
Universiti Putra Malaysia  
(Member)

**JUMIAH HASSAN, PhD**

Lecturer  
Faculty of Science  
Universiti Putra Malaysia  
(Member)



---

**AINI IDERIS, PhD**  
Professor/Deputy Dean  
School of Graduate Studies  
Universiti Putra Malaysia

Date: **15 JUL 2005**

## DECLARATION

I hereby declare that the thesis based on my original work except for quotations and citations which have been duly acknowledged. I also declare that it has not been previously or concurrently submitted for any other degree at UPM or other institutions.



---

**ABDALLA IMHMED BAHBOH**

Date: 17 / june 2005

## TABLE OF CONTENTS

	Page
<b>DEDICATION</b>	ii
<b>ABSTRACT</b>	iii
<b>ABSTRAK</b>	v
<b>ACKNOWLEDGEMENTS</b>	vii
<b>APPROVAL</b>	viii
<b>DECLARATION</b>	x
<b>LIST OF TABLES</b>	xiv
<b>LIST OF FIGURES</b>	xv
<b>LIST OF PLATES</b>	xviii

## CHAPTER

<b>I</b>	<b>INTRODUCTION</b>	1
	The Electrostatic Field in Dielectric Media	1
	The Interaction Between Electromagnetic Field and Wood	2
	Polarization of Wood	3
	Sensors	6
	Sensors Classification	6
	Capacitive Sensors	7
	Medium-Frequency Range (Bridges) Balance	9
	Tomography Imaging	10
	Ionizing Radiation Computed Tomography	10
	Microwave Imaging	11
	Ultrasonic Imaging	12
	Electrical Impedance Tomography	13
	Present Work	15
	Objectives	16
 <b>II</b>	 <b>LITERATURE REVIEW</b>	 18
	Tomographic Techniques	18
	Transverse Plane Impedance Imaging	19
	Parallel Current Lines	19
	Finite Difference Method	19
	Perturbation Method	20
	Applied Potential Tomography	20



	Adaptive Currents	20
	Electrical Capacitance Tomography	21
	Electrodes	22
	Materials	22
	Metals	22
	Carbon	23
	Adhesive Polymers	23
	Impedance Versus Frequency	23
	Size and Geometries	24
	Area	24
	Geometry	24
	Guard Electrode	25
	Electrical Moisture Meter	25
	Resistance Moisture Meter	25
	Dielectric Moisture Meter	26
	Dielectric Properties Of Wood	27
	Measurement Of Dielectric Properties of Wood	28
	Low Frequency	28
	High Frequency	29
	Super High Frequency	29
<b>III</b>	<b>THEORY</b>	31
	Dielectric Polarization	32
	Basic Equations on Dielectric Theory	34
	Effect of DC Conduction	41
	Capacitive Sensing	41
	Specimens and Electrodes for Solid Dielectrics	42
	Thévenin Equivalent Circuit for A Deflection Bridge	43
<b>IV</b>	<b>METHODOLOGY</b>	46
	General Description of The System	46
	Sensor Plate Design	57
	The Bridge and Amplifying Stage Circuits	58
	The Amplification Stag	51
	Instrumentation Amplifier	52
	Shielding	53
	The Whole Sensor Assembly	54
	Preparation of Samples	55
	Scanning of the Sample	57
	Interfacing and Acquisition	58
	The Equipments	60
<b>V</b>	<b>RESULTS AND DISCUSSION</b>	62
	Dispersion Process with Low Frequency at Normal M.C	62
	Testing Results of the Probe	66

Results After Calibration	70
Fiberboard	70
Sample Particleboard	70
Sample MDF-Board	75
Rubber Wood	83
Defects	84
Thickness	86
 <b>VI CONCLUSION AND SUGGESTIONS</b>	 89
Conclusion	89
Further Improvement	91
 <b>REFERENCES</b>	 93
<b>APPENDICES</b>	100
<b>BIODATA OF THE AUTHOR</b>	115



**LIST OF TABLES**

Table		Page
4.1	Normalized Capacitance Against Output Voltage at Different Resistance Ratios	53
5.1	Experimental Values of Measured Capacitance and Moisture Content at Three Locations of Rubber Wood Sample	81



## List of figures

Figure	Page
1.1 In A Capacitive Sensor, The Outer Guard Ring is Kept at the Same Voltage as the Inner Sensing Plate	8
1.2 Schering Bridge	10
3.1 Different Types of Dielectric Dispersion Behavior	40
3.2 Thevenin Equivalent Circuit for A Deflection Bridge	43
3.3 Deflection Bridge with Sensor Component C1.	45
4.1 Block Diagram of the General Tomography Imaging System	46
4.2 Three Electrode Sensor.	47
4.3 The Source Circuit Diagram for the Bridge Circuit	48
4.4 The Bridge Circuit with the Instrumentation Amplifier	49
4.5 The Bridge Circuit for Measuring the Variation in Capacitance for the Test Board	50
4.6 The Sensitivity and Linearity Plot for Different Resistor Ratios	51
4.7 Basic Circuit Diagram of RS AD521AD Ins. Amplifier	53
4.8 Schematic Shows the Scanning Procedure	57
4.9 Front Panel Window	59
4.10 Diagram Window of the program	60
5.1 The Quasi-dc Relaxation is Characterized by Two Independent Processes, Below and Above A Certain Characteristics Frequency $\omega_c$ For (a) MDFboard, (b) MERboard and (c) Particleboard	64
5.2 Equivalent Circuit for Fitting the Experimental Results	66
5.3 Capacitance Profile of Wood Slab Using Probe at 1.0 kHz	67
5.4 Output Profile of the Wood Slab, (a) With $r = 30$ mm Probe.	





(b) With $r = 10$ mm Probe.	68
5.5 Dielectric Properties of Profile Of Wood Sample 3, (a) Dry Wood. (b), After Adding 4 Water Drops to the Edges	69
5.6 Capacitance Profile for Particleboard Sample 10mm with Average Moisture Content of (a) 46 % (b) 26% (c) 15% (d) 10% w.b, At 5 KHz Color Bar Represents the Value Of Capacitance In pF.	71
5.7 Capacitance Versus Moisture content Of MerBoard HD900 With 9mm Thick at Four Different Frequencies. [At Place (a)]	73
5.8 Capacitance Versus Moisture Content of MerBoard HD900 With 9mm Thick at Four Different Frequencies. [At Place (b)]	74
5.9 Capacitance Versus Moisture Content of MerBoard HD900 With 9mm Thick at Four Different Frequencies. [At Place (c)]	74
5.10 Capacitance Versus Frequency for Eight Different Thicknesses of the Sample MDF-Board	75
5.11 Converted Dielectric Constant Versus Frequency for Eight Different Thicknesses of the Sample MDF-Board	76
5.12 For Each Thickness of the Eight, Frequency Against Capacitance, and for More Details, Graphs are Plotted Separately, a, b, c, d, e, f, g And h,	77
5.13 Capacitance Versus Moisture Content % Of MDF-Board, 3mm Thickness at Four Different Frequencies	81
5.14 Capacitance Versus Moisture Content % of MDF-Board 6mm Thickness at Four Different Frequencies	82
5.15 Capacitance Versus Moisture Content % Of MDF-Board 9mm Thickness at Four Different Frequencies	82
5.16 Capacitance Against Moisture Content Percentage for Rubber-Wood 15mm Samples	83
5.17 The Two Knots Appear as Big One, This is Due to Bigger Sensing Plate of the Sensor A High Capacitance	85
5.18 The Two Knots Appear Separated Using the Small Sensing Plate Sensor B with Losing Resolution	86

5.19 Contour profile of the Different Three Preformed Thicknesses  
of MDFboard Sample, Thinner Thickness Gives Higher Capacitance  
Value and Vice Versa

87

## LIST OF PLATES

Plate	Page
4.1.a Top View of Sensor A	54
4.1.b Bottom View of Sensor A	55
4.2 Wood Samples Used to Study Wood Characteristics Under Low Frequency range. From Left to Right A.Exelca, Pine, and Rubber Wood	56
4.3 Experimental Setup (Sensor A)	58
4.4 Experimental Setup (Sensor B), Two Voltmeters to the Left And to the Right and the Digital-Analog Training System	61
5.1: Samples From Left to Right, Particleboard, MER-Board and MDF-Board Used to Study Frequency Dispersion	63
5.2: The SI 1255. HF Frequency Analyzer	63
5.3: Rubber Wood	69
5.4 Sample Particleboard	71
5.5 Sample Pinewood	85



## **CHAPTER I**

### **INTRODUCTION**

#### **THE ELECTROSTATIC FIELD IN DIELECTRIC MEDIA**

An ideal dielectric material is one which has no free charges. Nevertheless, all material media are composed of molecules, these in turn being composed of charged entities (atomic nuclei and electrons), and the molecules of the dielectric are certainly affected by the presence of an electric field. The electric field causes a force to be exerted on each charged particle, positive particles being pushed in the direction of the field, negative particles oppositely, so that the positive and negative parts of each molecule are displaced from their equilibrium positions in opposite directions. These displacements, however, are limited (in most cases to very small fractions of a molecular diameter) by strong restoring forces which are set up with the changing charge configuration in the molecule. The overall effect from the macroscopic point of view is most easily visualized as the displacement of the entire positive charge of the dielectric relative to the negative charge. The dielectric is said to be polarized.

A polarized dielectric, even though it is electrically neutral on the average, produced an electrical field, both at exterior points and inside the dielectric as well. As a result, we are confronted with what appears to be an awkward situation: the polarization of the dielectric depends on the total electric field in the medium, but a part of the electric field is produced by the dielectric itself. Furthermore the distant electric field of the dielectric

may modify the free charge distribution on conducting bodies, and this in turn will change the electric field in the dielectric.

## **THE INTERACTION BETWEEN ELECTROMAGNETIC FIELD AND WOOD**

Wood is a natural material with a complex structure and composition. Interaction between the alternating electromagnetic field and wood makes it possible to elucidate specific properties of this material. The electromagnetic field consists of two components: electric and magnetic fields. The influence of these components on wood is different. The influence of the magnetic on wood is negligible and is not taken in consideration for practical purposes. The influence of the electric field on wood is very strong as the interaction between them results in the creation of electrical currents in the material.

Under the action of alternating electric field, the wood reveals its dielectric properties, which more often are characterized by two main indices: by the dielectric constant ( $\epsilon$ ) and by the dielectric loss tangent ( $\operatorname{tg}\partial$ ). The dielectric constant of a material shows how many times the force of interaction between the electric charges in the given medium is less than that in a vacuum. The dielectric constant of wood is equal to ratio of the capacity a condenser with the separator made of wood and the capacity of the vacuum capacitor of the same dimension and form (Torgovnikov, 1993).

The dielectric loss tangent of wood defines the part of the power applied to the wood that is absorbed by the material under the influence of the electric field. This part of the power is known to be transformed into thermal energy. The loss tangent is numerically equal to the ratio between the active current and the reactive current in the material or to the real and reactive powers ratio. One additional index is used in order to characterize the dielectric properties of wood and wood materials, viz. the dielectric loss factor  $\varepsilon''$ .  $\varepsilon' \cdot \tan \delta$ . The values of  $\varepsilon'$ ,  $\varepsilon''$ , and  $\tan \delta$  are always dimensionless, and their magnitude does not depend on the chosen system of units or the form of the equations.

### **Polarization Phenomena of Wood**

All materials are divided into three electrical groups: conductors, dielectric, and semiconductors. The conductors are characterized as materials with considerable electronic and ionic conductivity values. The dielectrics differ from the conductors by their low specific conductivity. Another principle distinction resides in the fact that the temperature coefficient of electric resistance of the dielectric is negative while that of the conductors is positive. Concerning the specific conductance, the semiconductors occupy an intermediate position between the dielectrics and conductors. By the character of the temperature dependence of conductivity, the semiconductors are close to the dielectrics.

It is assumed that conductors have a specific resistance in the range from about  $10^{-8}$  to  $10^{-5}$  ohm.m, semiconductors in the range from  $10^{-6}$  to  $10^{+9}$  ohm.m, and

dielectrics in the range from  $10^{+7}$  to  $10^{+17}$  ohm.m (Tareev 1982). Oven-dry wood has specific resistance ranging from  $10^{13}$  to  $10^{15}$  ohm.m and is classified as a polar dielectric. As the wood moisture content increases, the specific resistance of wood becomes lower, and its conductivity approaches that of the semiconductors. When the moisture content exceeds the cell wall's saturation point, the wood may have an ionic conductance. Under the influence of an electromagnetic field, the electric properties of wood are defined by polarization processes that take place because of the interaction between the molecules of the wood substance and the external field. In this case, moist wood as well as dry wood are considered polar dielectrics.

One of the most important intrinsic properties of wood is its polarization ability. The polarization effect caused by the change in the arrangement in the space of the electrically charged particles of the wood substance under the influence of an external electric field. Under this condition, wood acquires an electrical moment.

In a theoretical examination of the properties of wood, an elementary volume is assumed to exist. This elementary volume should comprise as many structural units as are necessary for considering (with due accuracy) the assumed volume of wood as a homogeneous body. At the same time the chosen volume should be sufficiently small so that the change in physical properties of the fields along its length could be neglected, and the properties can be considered uniform.

Sobloev (1979) proposed that substance elements of a size above 0.1mm should be regarded as macrostructural elements of wood. According to this suggestion, this category should be attributed such elements as layers of early wood and latewood, rays of medium and large width, large resin canals, and large vessels. In this case, the assumption that the elementary volume should be not less than  $\text{cm}^3$  can be accepted. This volume should comprise a sufficient quantity of macroelements, and the indices of physical properties of the specimen should reflect not only the combined properties of the microelements but also the properties of the macroelements. When investigating the dielectric properties of wood, it is necessary to take into account the macrostructure of the wood and therefore the samples size should be equal to or larger than the macrostructural elementary volume, i.e.,  $\geq 1 \text{ cm}^3$  (Torgovnikov, 1993).

Since the polarization of the material requires the displacement of particles, each having a finite mass, it is clear that the strength of the polarization must decrease with increasing frequency. That is, the particle's inertia tends to prevent it from "following" rapid oscillations in the applied field. The existence of several different types of polarization makes a complete analysis somewhat involved. For a qualitative understanding of polarization, however, it is sufficient to consider only the electronic polarization and to note that the other types exhibit a similar frequency response.

In the analysis of the electronic polarization, it is convenient to regard the heavy positive nucleus as being fixed in space and surrounded by an electron cloud of charge  $e$  and mass  $m$  which oscillates back and forth in response to the applied electric field  $E$ , the electron cloud moves in response of three forces: the force due to the applied field, the



restoring force due to the coulomb attraction of the positive nucleus, and frictional forces which result in dissipation of energy and consequent damping of oscillations.

## **Sensors**

In a measurement system the sensor is chosen to gather information about the measured quantity and convert it to an electric signal. A priori it would be unreasonable to expect the sensor to be sensitive to only to the quantity of interest and also to expect the output signal to be entirely due to the input signal. No measurement is ever obtained under ideal circumstances; therefore we must address real situation.

## **Sensors Classification**

A great number of sensors are available for different physical quantities. In order to study them, it is advisable first to classify sensors according to some criterion.

In considering the need for the power supply, sensors are classified as modulating or self-generating. In modulating (or active) sensors most of the output signal power comes from an auxiliary power source. The input only controls the output. Conversely, the self-generating (or passive) sensors output power comes from the input.

In considering output signals, we classify sensors as analog or digital. In analog sensors the output is changes in a continuous way at a macroscopic level. The information is